



IJEAST

INTERNATIONAL JOURNAL
OF ENGINEERING APPLIED SCIENCE
AND TECHNOLOGY



VOLUME : 2 ISSUE : 4 Print / Issue Publication Date: 31-Mar-2017



ISSN : 2455-2143



Indexed In



WWW.IJEAST.COM

editor@ijeast.com



CASE STUDY OF 64-BIT LOW POWER PARALLEL PREFIX ADDER FOR HIGH SPEED ARITHMETIC CIRCUITS

Mr. Nikhil Shrivastav
GVIET, Banur,
Punjab, India

Abstract-- The addition of two binary numbers is the basic and most often used arithmetic operation on microprocessors, digital signal processors and data processing application specific integrated circuits. Parallel prefix adder is a general technique for speeding up binary addition. This method implements logic functions which determine whether groups of bits will generate or propagate a carry. The proposed 64-bit adder is designed using four different types prefix cell operators, even-dot cells, odd-dot cells, even-semi-dot cells and odd-semi-dot cells; it offers robust adder solutions typically used for low power and high-performance design application needs. The comparison can be made with various input ranges of Parallel Prefix adders in terms power, number of transistor, number of nodes. Tanner EDA tool was used for simulating the parallel prefix adder designs in the 250nm technologies.

Keywords--Low Power VLSI; Parallel Prefix Adder; dot operators; 64-bit Parallel Prefix Adder;

I. INTRODUCTION

The parallel adder is the most important element used in arithmetic operations of many processors. With the rising popularity of mobile devices, low power consumption and high performance integrated circuits has been the target of recent research. However, the two design criteria are often in conflict and that improving one particular aspect of the design constrains the other. Extends from the idea of carry look-ahead computation, a class of parallel carry look-ahead schemes are formed targeting at high-performance applications. A Parallel Prefix Adder (PPA) is equivalent to the CLA adder [2]. The two different in the way their carry generation block is implemented. The parallel prefix carry-look ahead adder was first proposed some twenty years ago as a means of accelerating n -bit addition in VLSI technology. It widely considered as the fastest adder and used for high performance arithmetic circuits in the industries. A three step process is generally involved in the construction of a Parallel Prefix Adder. The first step involves the

creation of generate and propagate signals for the input operand bits. The second step involves the generation of carry signals. In the final step, the sum bits of the adder are generated with the propagate signals of the operand bits and the preceding stage carry bit using a xor gate. The figure 1 shows the three step process is generally involved in the construction of a Parallel Prefix Adder.




Figure 1. Steps in parallel prefix adder

II. EXISTING PARALLEL PREFIX ADDERS

The arrangement of the prefix network specifies the type of the PPA. The Prefix arrangement described by Haiku Zhu, Chung-Kuan Cheng and Ronald Graham, has the minimal depth for a known 'n' bit adder. Best logarithmic adder structures with a fan-out of two for minimizing the area-delay product is presented by Matthew Ziegler and Mircea Stan. The Sklansky adder presents a least depth prefix network at the cost of increased fan-out for certain computation nodes [8]. The algorithm invented by Kogge-Stone has both optimal depth and low fan-out but produces massively complex circuit realizations and also account for large number of interconnects [9]. Brent-Kung adder has the merit of minimal number of computation nodes, which yields in reduced area but structure has maximum depth



which yields slight increase in latency when compared with other structures. The Han-Carlson adder combines Brent-Kung and Kogge-Stone structures to achieve a balance between logic depth and interconnect count. Knowles presented a class of logarithmic adders with minimum depth by allowing the fan-out to grow [4]. Ladner and Fischer proposed a general method to construct a prefix network with slightly higher depth when compared with Sklansky topology but achieved some merit by reducing the maximum fan-out for computation nodes in the critical path [6]. Sparse tree binary adder proposed by Yan Sun and et al., combines the benefits of prefix adder and carry save adder [3][10]. Integer Linear Programming method to build parallel prefix adders is proposed by Jainhau Liu and et al., The proposed Parallel Prefix adder for 64-bits has been proposed.

III. PREFIX OPERATORS

In the above equation, ‘•’ operator is applied on two pairs of bits and. These bits represent generate and propagate signals used in addition [7]. The output of the operator is a new pair of bits which is again combined using a dot operator ‘•’ or semi-dot operator ‘•’ with another pairs of bits. This procedural use of dot operator ‘•’ and semi-dot operator ‘•’ creates a prefix tree network which ultimately ends in the generation of all carry signals. In the final step, the sum bits of the adder are generated with the propagate signals of the operand bits and the preceding stage carry bit using a xor gate. The semi-dot operator ‘•’ will be present as last computation node in each column of the prefix graph structures, where it is essential to compute only generate term, whose value is the carry generated from that bit to the succeeding bit.

$$\begin{aligned} (P_i, G_i) \bullet (P_{i-1}, G_{i-1}) &= (P_i \cdot P_{i-1}, \\ G_i + P_i \cdot G_{i-1}) & (P_i, G_i) \bullet (P_{i-1}, G_{i-1}) \\ &= (G_i + P_i \cdot G_{i-1}) \end{aligned}$$

These two operators are divided into four types of different types prefix operators [5].

IV. PROPOSED 64-BIT PARALLEL PREFIX ADDER

A. 32-Bit Parallel Prefix Adder

Figure 2 shows the design of the proposed 32-bit parallel prefix adder. The objective is to eliminate the huge overlay between the prefix sub-terms being calculated. Hence the associate property of the dot operator is working to retain the number of computation

nodes at a minimum [1]. The first stage of the computation is called as pre-processing. The first stage in the architectures of the 32-bit prefix adder involve the creation of generate and propagate signals for individual operand bits in active low format. The second stage in the prefix addition is termed as prefix computation. This stage is responsible for creation of group generates and groups propagate signals. The stages with odd indexes use odd-dot and odd-semi-dot cells where as the stages with even indexes use even-dot and even-semi-dot cells.

B. 64-Bit Parallel Prefix Adder

The Proposed 64-bit parallel prefix adder has ten stages of implementation. CMOS logic family will implement only inverting functions. Thus cascading odd cells and even cells alternatively gives the benefit of elimination of two inverters between them, if a dot or a semi-dot calculation node in an odd stage receives both of its input edges from any of the even stages and vice-versa. But it is essential to introduce two inverters in a path, if a dot or a semi-dot computation node in an even stage receives any of its edges from any of the even stages and vice-versa. From the prefix graph of the proposed structure shown in Figure 3, we assume that there are only few reduction, since these inverters if not eliminated, would have contributed to significant amount of power dissipation due to switching.

The output of the odd-semi-dot cells gives the value of the carry signal in that corresponding bit position. The output of the even-semi-dot cell gives the complemented value of carry signal in that corresponding bit position.




Figure 2. 32-Bit Parallel Prefix Adder




Figure 3. 64-Bit Proposed Parallel Prefix Adder

The final stage in the prefix addition is termed as post-processing. The final stage involves generation of sum bits edges with a pair of inverters, to make (G, P) as (G', P') as (G, P) respectively. The pair of inverters in a path is represented by a diamond in the prefix graph. By introducing two cells for dot operator and two cells for semi-dot operator, we have eliminated a large number of inverters. Due to inverter elimination in paths, the propagation delay in those paths would have reduced. Further we achieve a benefit in power bits and the carry bits generated in true form or complement form. The first stage and last stage are intrinsically fast because they involve only simple operations on signals local to each bit position. The intermediate stage embodies long distance propagation of carries, so the performance of the adder depends on the intermediate stage.

V. SIMULATION RESULTS

C. Proposed 64-Bit PPA




Figure 4. Block diagram for Proposed 64-Bit Parallel Prefix Adder



Figure 5. Output Waveform for Proposed 64-Bit Parallel Prefix Adder



Figure 6. Output Waveform for Proposed 64-Bit Parallel Prefix Adder



D. Comparison Charts

1) Power Comparison

The power comparison shows that, when number of input bits increased the power consumed by the adder will also increasing.

Table 1. POWER COMPARISION IN DIFFERENT VOLTAGE LEVEL

Adder	At V=5	At V=4	At V=3	At V=2
8-bit	4.45	2.51	.0090	0.002
16-bit	11.6	5.21	1.91	0.579
32-bit	20.0	8.82	3.03	0.804
64-bit	44.1	21.2	7.84	2.30




Figure 7. Power Comparison

2) Number of Nodes




Figure 8. Number of Nodes




Figure 9. Number of Transistors

The above comparison graph shows the comparison of nodes and transistors in the 64-bit parallel prefix adder design.

VI. CONCLUSION

The parallel prefix formulation of binary addition is a very convenient way to formally describe an entire family of parallel binary adders. The proposed low power 64-bit parallel prefix adder were designed by using the four different prefix cell operators and compared with existing parallel prefix adders such as 8-bit PPA, 16-bit PPA, and 32-bit PPA. The performances in terms of Power, Number of nodes, Number of Transistor tradeoffs for various input ranges were analyzed. The power comparison can be made by varying the supply voltage from 1 to 5 for the entire parallel prefix adder designed. For 64-bit low power Parallel Prefix Adder Seventeen stages were used for generating the sixty three carries outputs and 1339 nodes were formed in the 64-bit low power Parallel Prefix Adder. The Proposed 64-bit low power prefix structure makes it more suited for Arithmetic Logic Units and multiplier units for complex ranges of input data computation. Tanner EDA tool was used for simulating the parallel prefix adder designs in the 250nm technologies.

VII. REFERENCES

- [1] P.Ramanathan, P.T.Vanathi, "Novel Power Delay Optimized 32-bit Parallel Prefix Adder for High Speed Computing", International Journal of Recent Trends in Engineering, Vol 2, No. 6, November 2009.
- [2] R. Zimmermann, Binary Adder Architectures for Cell-Based VLSI and their Synthesis, ETH Dissertation 12480, Swiss Federal Institute of Technology, 1997.
- [3] David Harris, "A Taxonomy of parallel prefix networks," Proceedings of the 37th Asilomar



- Conference on Signals, Systems and Computers
Pacific Grove, California, pp.2213-2217, November
2003.
- [4] S.Knowles, "A family of adders", Proceedings of the
15th IEEE Symposium on Computer Arithmetic. Vail,
Colorado, pp.277-281, June
2001.
- [5] P.Ramanathan, P.T.Vanathi, "A Novel Logarithmic
Prefix Adder with Minimized Power Delay Product",
Journal of Scientific & Industrial Research, Vol. 69,
January 2010, pp. 17-20.
- [6] R. Ladner and M. Fischer, "Parallel prefix
computation," Journal of
ACM. La Jolla, CA, vol.27, no.4, pp. 831-838,
October 1980.
- [7] Andrew Beaumont-Smith and Cheng-Chew Lim,
"Parallel Prefix Adder Design", Department of
Electrical and Electronic Engineering, the University
of Adelaide, 2001.
- [8] J. Sklansky, "Conditional sum addition logic,"
IRE Transactions on
Electronic computers. New York, vol. EC- 9, pp. 226-
231, June 1960.
- [9] P.Kogge and H.Stone, "A parallel algorithm for the
efficient solution of a general class of recurrence
relations," IEEE Transactions on Computers, vol.
C-22, no.8, pp.786-793, August 1973.
- [10] R.Brent and H.Kung, "A regular layout for parallel
adders," IEEE Transaction on Computers, vol. C-31,
no.3, pp. 260-264, March 1982.
- [11] T. Han and D. Carlson, "Fast area efficient VLSI
adders," Proceedings of the Eighth Symposium on
Computer Arithmetic. Como, Italy, pp.49-
56, September 1987.

IJEAST

INTERNATIONAL JOURNAL OF ENGINEERING APPLIED SCIENCE AND TECHNOLOGY



AUTHORS

Mr. Nikhil Shrivastav



ABOUT IJEAST

International journal of Engineering Applied Science and Technology (IJEAST) is a peer-reviewed, open access journal that publishes high - quality research paper in the field of Engineering, Applied Science and Technology.

IJEAST aims to provide a platform for researchers, academicians, and professionals to share their innovative ideas, research findings, and practical experiences with the global scientific community.

JOURNAL METRICS



H-INDEX

33



i10-INDEX

154



IJEAST
CITATIONS

9,647

(IJEAST CITATIONS)



PEER-REVIEWED
& OPEN ACCESS

PUBLISHED
MONTHLY



PEER REVIEWED

All submission are rigorously peer reviewed to ensure quality.



AUTHORS ARE OUR PRIORITY

We value our authors and recognize their contribution to the advancement of research and knowledge.



OPEN ACCESS

Free and unrestricted access to research for all.



GLOBAL REACH

Connecting researchers and professionals worldwide.



TIMELY PUBLICATION

We ensure a swift and efficient publication process.



For more information, visit our website
www.ijeast.com



editor@ijeast.com



www.ijeast.com



India



2455-2143